

## **Customizing the remote software**

The remote software has the ability to have a different startup screen, default language and detector names. This enables agents or resellers to stamp their own identity on the product. The following instructions describe how to create a custom version of the remote software.

REMOTE2K.INI and SETUP.INI on the install disk contain many details about the software configuration and this is where user customization of language is done. To modify these settings edit REMOTE2K.INI or SETUP.INI with a text editor. Any sections not detailed here should not be modified as this may cause incorrect operation of the remote software.

### **Setting a custom web site**

Selecting Help/About in the remote software shows the About dialog which shows details of program information and also a link to a web site that customers can click on to take them directly to the site. The URL (address on the internet) of this site can be modified to point to the site of the agent or reseller in REMOTE2K.INI. Note that 'http://' must prefix the address or the web link feature will not work.

```
[User]  
WebSite=http://www.airsensetechnology.com
```

If a WebSite entry does not exist in REMOTE2K.INI the AirSense Technology Ltd web site URL is displayed.

### **Setting a custom start-up logo**

LOGO.BMP contains the start-up logo and this may be replaced with any standard Windows bitmap. The start-up bitmap window is sized to the bitmap so any bitmap size can be used.

## Setting custom detector names

To rename the detector product names the section [DetectorNames] must be created as it does not exist in the standard REMOTE2K.INI. Example entries for a section defining the default names are shown below. To use alternative names replace the text after the equals sign. If the section does not exist the standard device names will be used.

```
[DetectorNames]
Name0=Unknown
Name1= Stratos-HSSD detector
Name2= MatrixScan cell
Name3= Stratos-Quadra
Name4= Contact monitor
Name5= PC command module
Name6= Stratos-HSSD 2 detector
Name7= Power supply
Name8= Command module
Name11= Stratos-Micra 25
Name12= Stratos-Micra 100
Name15= Stratos-Ex
Name19= Stratos-Nano
```

## Setting a custom default language

To set a custom language set the language statement, shown below, to the required language number. This is set in SETUP.INI. This will be the default displayed language during installation provided that the software is not already installed. If the software is already installed then the current language set in the installed program is used as the default language.

```
[Product]
Language=0
```

The available languages are shown below. Please note that the languages may not be fully translated at this time.

number	language
0	English
1	Estonian
2	Dutch
3	French
4	German
5	Hungarian
6	Italian
7	Norwegian
8	Portuguese
9	Spanish
10	Swedish
11	English US (non-metric units)
12	Finnish
13	Korean
14	Simplified Chinese
15	Traditional Chinese

## Changing the program name

The following two settings are stored in SETUP.INI. By editing SETUP.INI you can change both the name of the remote software and the install directory.

```
[Software]
Description=Remote 2.0
```

Changing the entry shown above will set a new name for the remote software. This name will be displayed on the title bar and also the program name on the control panel Add/Remove programs list. It is not recommended that the version number is modified.

```
[Group]
Files=2
File1=REMOTE2K.EXE,Remote 3
File2=README.TXT,Remote 3 ReadMe
```

The entries shown above set the icon names for the program and readme file. To change the displayed name for an icon change the text after the comma.

## Changing the install directory

The following setting is stored in SETUP.INI. By editing SETUP.INI you can change the install directory.

```
[Directories]
InstallDir=C:\remote2k
```

Changing the entry shown above will set a new install directory. ***Note that long file paths are not supported for the directory names.***